

CH34X USB-to-SERIAL MACOS DRIVER INSTALLATION INSTRUCTION

Version: V1G

<http://wch.cn>

Introduction

This installation guide document shows the procedure of installing the macOS driver for the WCH USB-to-SERIAL devices. The driver can be downloaded from the website:

Link: http://www.wch.cn/downloads/CH34XSER_MAC_ZIP.html

System Requirement


- OS X 10.9 to OS X 10.15
- OS X 11.0(Big Sur) and above


Chip Model Support

- CH340/CH341/CH343/CH9101/CH9102/CH9143 (USB to Single Serial Port)
- CH342/CH344/ CH347/CH9103 (USB to Multi Serial Ports)

Installation

1. Download the driver from the website and unzip the file to a local installation directory.
2. Click on the driver file and continue to proceed step by step.





When using OS X 11.0 and above, you need to perform the following additional operation:
Open "LaunchPad" and find "CH34xVCPDriver" Application, open the App and click the "Install" button.



When using OS X 10.9 to OS X 10.15, you need to click "Restart" to restart your computer, then perform the following steps after restarting.



- When plug the USB-to-SERIAL device into the USB port, you can open “System Report”->Hardware->USB, the right side is “USB Device Tree” and you will find a device whose “Vendor ID” is [0x1a86] if USB device is working properly.



- Open “Terminal” program under Applications-Utilities folder and type the command “ls /dev/tty*”.




You should see the “tty.wchusbserialx” where “x” is the assigned device number similar to Windows COM port assignment.

Note:

macOS High Sierra 10.13 introduces a new feature that requires user’s approval before loading new third-party kernel extensions.

Link: <https://developer.apple.com/library/content/technotes/tn2459/index.html>

Please forward to “System Preferences”->“Security & Privacy”->“General” page, below the title “Allow apps downloaded from:” choose the choice 2->“Mac App Store and identified developers” so that driver will work normally.



Uninstall Driver

- OS X 10.9~10.15
Open "Terminal" program under Applications-Utilities folder and type the following commands:
sudo rm -rf /Library/Extensions/CH34xVCPDriver.kext
sudo rm -rf /var/db/receipts/*CH34xVCPDriver*.*
- OS X 11.0 and above
 - 1.Remove the Application to "Trash" to uninstall.
 - 2.Restart the computer before reinstalling the driver.